

# SPD-703-1

## G.703 Rate and Interface Converter



### FEATURES

- Converts between G.703 Codirectional interface and V.24/RS-232, V.35, V.36/RS-422, X.21, RS-530 or Ethernet
- Performs 48 kbps or 56 kbps to 64 kbps rate conversion
- Operates with selectable timing source
- Meets G.823 jitter requirements
- Supports ITU V.54 and V.52 diagnostics
- ITU V.110 compatible (56 kbps to 64 kbps conversion)
- Supports additional 1.2 kbps asynchronous subchannel
- Includes line protection circuits

### DESCRIPTION

- SPD-703-1 rate and interface converter enables communication between devices with G.703 Codirectional (64 kbps) and several other standard communication interfaces.
- SPD-703-1 performs two types of conversion:
  - Interface conversion from G.703 Codirectional to V.24, V.35, V.36, X.21, RS-530 or Ethernet
  - Rate conversion from 48 kbps or 56 kbps to 64 kbps.
- SPD-703-1 recovers receive timing from the G.703 signal. The transmit timing is user-selectable for:
  - Recovered clock from the G.703 receive signal
  - Internal timingTwo internal 16-bit elastic buffers accommodate for the difference in clocking phase.
- When operating at 64 kbps, SPD-703-1 has a range of up to 0.8 km (0.5 mile) from the G.703 equipment.

- SPD-703-1 supports activation of local analog, remote digital and local digital loopbacks in compliance with ITU V.54 requirements. The loopbacks are activated either via the front panel pushbuttons or the DTE interface (except for X.21 and Ethernet interfaces). In addition, SPD-703-1 generates and tests a pseudo-random test pattern according to ITU V.52 standard.
- When operating at 48 kbps or 56 kbps, SPD-703-1 transfers RTS to DCD control signal end-to-end. Alternatively, the available bandwidth can be used for a 1.2 kbps async subchannel for connecting additional DTE equipment over the same link.
- SPD-703-1 is available either as a standalone unit or as a card for ASM-MN-214, 19-inch modem rack.

# SPD-703-1

## G.703 Rate and Interface Converter

### SPECIFICATIONS

#### G.703 INTERFACE

- **Type**  
Codirectional, 64 kbps
- **Line**  
4-wire, 19 AWG to 26 AWG
- **Range**  
Up to 0.8 km (0.5 mile) over 24 AWG line
- **Impedance**  
120Ω nominal
- **Balance**  
Better than 45 dB (up to 256 kHz)  
Better than 35 dB (up to 384 kHz)
- **Return Loss**  
Better than 20 dB (up to 256 kHz)  
Better than 14 dB (up to 384 kHz)
- **Clock Frequency**  
64 kHz
- **Frequency Tracking**  
±500 ppm
- **"Pulse" Amplitude**  
1.0V nominal
- **"Zero" Amplitude**  
0V ±0.1 max
- **Jitter Performance**  
According to G.823 requirements
- **Connector**  
5-clip terminal block

#### DTE INTERFACE

- **Type**
  - V.24/RS-232: 25-pin, D-type, female
  - V.35: 34-pin, female
  - V.36/RS-422: 37-pin, D-type, female (via adapter cable)
  - X.21: 15-pin, D-type, female
  - RS-530: 25-pin, D-type, female
  - Ethernet: RJ-45 or two BNC
- **Data Rate**  
48 kbps, 56 kbps or 64 kbps

- **Spare Bandwidth Utilization**  
Available when operating at 48 kbps or 56 kbps:
  - Additional 1.2 kbps async channel
  - Transfer of RTS to DCD control signal end-to-end
  - Fixed "1" to guarantee "1"s density over T1 network

#### GENERAL

- **Timing**  
Receive (LBT), derived from G.703 receive pair:
  - RC and TC from SPD-703-1 to a DTE
  - RC from SPD-703-1 and TC from an external tail modem
  - RC and TC from an external DCE to SPD-703-1External (EXT): from the DTE  
Internal (INT): from internal source
- **Diagnostics**  
V.54 loopbacks:
  - Local analog (ANA), activated via front panel or from DTE
  - Remote digital (REM), activated via front panel or from DTE
  - Local digital (DIG), activated via front panelBERT:  
Internal pattern generator and tester in compliance with V.52

*Note: ANA and REM loopback activation from the DTE is not available for X.21 and Ethernet interfaces.*

- **Physical**  
Height: 4.4 cm / 1.7 in  
Width: 21.5 cm / 8.5 in  
Depth: 24.0 cm / 9.6 in  
Weight: 1.4 kg / 3.1 lb
- **Power**  
AC: 115 or 230 VAC (±10%), 47 to 63 Hz, 5W  
DC: 24 (18 to 32 VDC) or -48 VDC (-42 to -57 VDC)
- **Environment**  
Temperature: 0–50°C/32–122°F  
Humidity: Up to 90%, non-condensing

### ORDERING

#### SPD-703-1/\*/#

G.703 rate and interface converter

#### SPD-703-1/R/#

G.703 rate and interface converter, card version for the ASM-MN-214 modem rack

\* Specify power supply:

**115** for 115 VAC

**230** for 230 VAC

**24** for 24 VDC

**48** for -48 VDC

# Specify DTE interface:

**V24** for V.24 interface

**V35** for V.35 interface

**V36** for V.36 interface

**530** for RS-530 interface

**X21** for X.21 interface

**UTP** for built-in Ethernet bridge with RJ-45 connector

**BNC** for built-in Ethernet bridge with two BNC connectors

#### CIA/&

Connector interface adapter for the ASM-MN-214 modem rack

& Specify connector type:

**V35/1** for adapting one modem rack 25-pin connector to one V.35 34-pin connector

**X21/1** for adapting one modem rack 25-pin connector to one X.21 15-pin connector

### APPLICATION



**RAD**

data communications

www.rad.com

• **International Headquarters**  
24 Raoul Wallenberg Street  
Tel Aviv 69719, Israel  
Tel: (972) 3-6458181  
Fax: (972) 3-6498250, 6474436  
Email: rad@rad.co.il

• **U.S. Headquarters**  
900 Corporate Drive  
Mahwah, NJ 07430  
Tel: (201) 529-1100  
Toll free: 1-800-444-7234  
Fax: (201) 529-5777  
Email: market@radusa.com

452-100-07/01